# **DC-DC Converters**

## DLS-4812DC-HW Series

48V to 12V DC Power Supply



- I High efficiency
- I High precision
- I Heavy duty applications

## DLS-4812DC-HW Series DC-DC Converter Datasheet 38-62 VDC Input and 12VDC output



### **Applications:**

- Automotive
- Telecommunications
- Distributed power
- Defense
- Aerospace
- Medical
- And other applications requiring high efficiency

#### **General Description:**

Nelso<sup>®</sup> is manufacturer of high precision, high reliability DC-DC Converter in Kolkata, India. This product is designed to provide 48V to 12V power conversion for heavy duty applications.

#### Features:

- Input-output isolation
- High efficiency
- High precision
- Wide input voltage range
- Over-voltage protection
- Under voltage protection
- Reverse polarity protection
- Voltage transient protection
- Over load protection
- Short circuit protection

#### Quick Reference Data:

Model No.	Input Voltage	Output Voltage	Output Current	Efficiency	Ripple
DLS-4812DC-HW	48V DC	12V DC	21-50A	>80%	<150mV

#### **Electrical Specification:**

Input Voltage:	38V - 62V DC		
Output Voltage:	12V DC (Regulated)		
Output Current / Wattage:	21 - 50A / 252W-600W		
Reverse Polarity:	100V DC		
Line Regulation:	±1%		
Load Regulation:	± 5% at terminal block		
Switching Frequency:	80 KHz		
Efficiency:	>80% Typical		
Topology:	Transformer isolated forward converter		
Operating Temperature:	-20 to 80 °C		
Humidity:	Up to 95% RH		
Cooling Process:	Forced convection cooling by fan		
Storage Temperature Range:	- 55°C to + 105°C		
Weight:	1400gm		
Dimension (Length x Width x Height):	242 x 155 x 95mm		

#### **Dimension and Pin Assignment**

